

## Korenix工业产品选择指南 - SFP 100Mbps BIDI/WDM



SFP100SM20B13  
SFP100SM20B13-W



SFP100SM20B15  
SFP100SM20B15-W




SFP100SM40B13  
SFP100SM40B13-W

100Mbps SFP for JetNet 5628G / 5010G / 5008G-P / 4510 / 4010

光纤收发器 &应用	单模 100Mbps BIDI/WDM, 20km	单模 100Mbps BIDI/WDM, 20km	单模 100Mbps BIDI/WDM, 40km
波长	TX 1310nm, RX 1550nm	TX 1550nm, RX 1310nm	TX 1310nm, RX 1550nm
发射功率	-14dBm(Min)~ -8dBm(Max)	-14dBm(Min)~ -8dBm(Max)	-8dBm(Min)~ 0dBm(Max)
接收灵敏度	0dBm ~ -32dBm(Max)	0dBm ~ -32dBm(Max)	0dBm ~ -34dBm(Max)
链路预算 (LinkBudget)	18dB	18dB	26dB
工作温度	-10°C~70°C -40°C~85°C (W)	-10°C~70°C -40°C~85°C (W)	-10°C~70°C -40°C~85°C (W)
存储温度	-40°C~85°C	-40°C~85°C	-40°C~85°C
工作湿度	85%	85%	85%



SFP100SM40B15  
SFP100SM40B15-W



SFP100SM60B13  
SFP100SM60B13-W



SFP100SM60B15  
SFP100SM60B15-W

100Mbps SFP for JetNet 5628G / 5010G / 5008G-P / 4510 / 4010

光纤收发器 &应用	单模 100Mbps BIDI/WDM, 40km	单模 100Mbps BIDI/WDM, 60km	单模 100Mbps BIDI/WDM, 60km
波长	TX 1550nm, RX 1310nm	TX 1310nm, RX 1550nm	TX 1550nm, RX 1310nm
发射功率	-8dBm(Min)~ 0dBm(Max)	-5dBm(Min)~ 0dBm(Max)	-5dBm(Min)~ 0dBm(Max)
接收灵敏度	0dBm ~ -34dBm(Max)	0dBm ~ -34dBm(Max)	0dBm ~ -34dBm(Max)
链路预算 (LinkBudget)	26dB	29dB	29dB
工作温度	-10°C~70°C -40°C~85°C (W)	-10°C~70°C -40°C~85°C (W)	-10°C~70°C -40°C~85°C (W)
存储温度	-40°C~85°C	-40°C~85°C	-40°C~85°C
工作湿度	85%	85%	85%